

Service Manual

Blu-ray Disc Player

Model No. **DMP-BD84PU**
DMP-BD84GN
DMP-BD84GA
DMP-BD84GH
DMP-BD94PU



Colour
(K).....Black Type

Please file and use this manual together with the service manual for Model No.DMP-BD73PU, DMP-BD73GC, DMP-BD83PU, DMP-BD83GN, DMP-BD83GA, DMP-BD83GT, DMP-BD83GJ, DMP-BD93PU, Order No.CHM1503008CE.

2 Replacement Parts List

2.1. Mechanical Replacement Parts List

Notes:

*Important safety notice:

Components identified by Δ mark have special characteristics important for safety.

Furthermore, special parts which have purposes of fire-retardant (resistors), high-quality sound (capacitors), low-noise (resistors), etc. are used.

When replacing any of components, be sure to use only manufacturer's specified parts shown in the parts list.

*Warning: This product uses a laser diode. Refer to caution statements.

*Capacity values are in microfarads (μ F) unless specified otherwise, P=Pico-farads (pF), F=Farads (F).

*Resistance values are in ohms, unless specified otherwise, 1K=1,000 (OHM), 1M=1,000k (OHM).

*The marking (RTL) indicates the retention time is limited for this item. After the discontinuation of this assembly in production, it will no longer be available.

**("IA)" marks in Remarks indicate languages of instruction manuals. [(IA): English]

*All parts are supplied by CHPAVC.

E.S.D. standards for Electrostatically Sensitive Devices, refer to "PREVENTION OF ELECTROSTATIC DISCHARGE (ESD) TO ELECTROSTATICALLY SENSITIVE (ES) DEVICES" section.

Notes:

*Parts indicated with "ADJ" in the Remarks column are necessary to Input Engineering Adjusted Value.

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
		■	CASING		
Δ	1	SKY0013T	BD DRIVE	1	ADJ
	2	SEP0405AA	OPERATION P.C.B.	1	(RTL) E.S.D.
	3	SUKB404AF1UT	DIGITAL P.C.B.	1	E.S.D. ADJ BD94PU
	3	SUKB404AB1NT	DIGITAL P.C.B.	1	E.S.D. ADJ BD84GN
	3	SUKB404AB1AT	DIGITAL P.C.B.	1	E.S.D. ADJ BD84GA/GH
	3	SUKB404AB1UT	DIGITAL P.C.B.	1	E.S.D. ADJ BD84PU
	4	C5ZZZ0000098	WIFI MODULE	1	BD94PU
	5	VEE1Q68	WLAN CABLE UNIT	1	BD94PU
	6	RGK2298-K	TRAY PANEL	1	
	7	RMX0503	SPACER	1	BD94PU
	10	RKA0243-KU	FOOT RUBBER	1	
	11	RKA0243-KU	FOOT RUBBER	1	
	12	RKA0243-KU	FOOT RUBBER	1	
	13	RKA0243-KU	FOOT RUBBER	1	
	14	RGF1736K-K	FRONT PANEL	1	BD94PU
	14	RGF1736M-K	FRONT PANEL	1	BD84GN/GA/GH/PU
	15	RGL0823-Q	LED SHEET	1	
	16	RGU2987-Q1	FUNCTION BUTTON	1	
	17	RKM0767-K	TOP CASE	1	
Δ	18	RGR0476A-M	BOTTOM CASE	1	BD94PU
	18	RGR0476B1C	BOTTOM CASE	1	BD84GN
	18	RGR0476B1D	BOTTOM CASE	1	BD84GA/GH
	18	RGR0476B1J	BOTTOM CASE	1	BD84PU

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	50	RHD30168-J	SCREW	1	
	51	RHD30168-J	SCREW	1	
	52	RHD30168-J	SCREW	1	
	53	RHD30168-J	SCREW	1	
	59	RHD30119-U	SCREW	1	
	60	RHD30119-U	SCREW	1	
	61	RHD30119-U	SCREW	1	
Δ	101	VQL2P54	LASER CAUTION LABEL	1	
	102	VMA0V86	YOKE	1	
	103	VMD6392-J	CLAMPER	1	
	104	VMD6881-2	TRAY	1	
	105	VMD6580	MID BASE	1	
	106	VDG1756-1J	PULLEY GEAR	1	
	107	VDG1757-J	MID GEAR	1	
	108	VEM0896-J	LOADING MOTOR U	1	
	109	VMD6390-J	SLIDE CAM	1	
	110	VMD6882-2	MECHA CHASSIS	1	
	111	VMG1720	BELT	1	
	112	VWJ2400-3	PICKOFF	1	
	113	VHD2268	NUT PIECE SCREW	1	
	114	VMB4004-J	NUT PIECE SPRING	1	
	115	VMD6754	NUT PIECE	1	
Δ	116	SXA0045-SER	OPU	1	ADJ
	117	KOL1CE000001	SWITCH	1	
	118	VWJ2482	SW FFC	1	
Δ	119	SXA0044-SER	TRAVERSE UNIT	1	
	119-1	L6KAYYYH0010	STEPPING MOTOR	1	
	119-2	VMS8126	SHAFT	1	
	119-3	VMB4682	SHAFT SPRING	1	
	119-4	VMB4682	SHAFT SPRING	1	
	119-5	XTN2+4FFJ	STEPPING MOTOR SCREW	1	
	119-6	XTN2+4FFJ	STEPPING MOTOR SCREW	1	
	119-7	VMG2037	DAMPER	1	
	119-8	VMG2037	DAMPER	1	
	119-9	VMG2037	DAMPER	1	
	119-10	VMG2037	DAMPER	1	
		■	ACCESSORY		
Δ	A1	SAE0010AA	AC ADAPTOR	1	BD94PU/84PU
Δ	A1	SAE0004AA	AC ADAPTOR	1	BD84GN
Δ	A1	SAE0002BA	AC ADAPTOR	1	BD84GA
Δ	A1	SAE0003AA	AC ADAPTOR	1	BD84GH
	A2	N2QAYB001026	REMOTE CONTROL UNIT	1	BD94PU/84PU
	A2	N2QAYB001029	REMOTE CONTROL UNIT	1	BD84GN
	A2	N2QAYB000958	REMOTE CONTROL UNIT	1	BD84GA/GH
	A3	RPFC0023-1	POLYETHYLENE BAG	1	
	A4	RPFC0125	POLYETHYLENE BAG	1	BD84GA/GH
Δ	A5	SQT1270	OPERATING INSTRUCTIONS	1	BD94PU/84PU
Δ	A5	SQT1274	OPERATING INSTRUCTIONS	1	BD84GN/GA/GH
	A12	RPQF0374	INSULATION BOARD	1	BD84GA
	A13	K2CQ2YY00126	AC CORD	1	BD94PU/84PU
	A15	K2DAYYY00002	POWER PLUG ADAPTOR	1	BD94PU/84PU
	A16	K1HY19YY0027	HDMI CABLE	1	
		■	PACKING		
	PC1	SPU0150	PACKING CASE	1	BD94PU
	PC1	SPU0154	PACKING CASE	1	BD84GN
	PC1	SPU0156	PACKING CASE	1	BD84GA

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	PC1	SPU0158	PACKING CASE	1	BD84GH
	PC1	SPU0149	PACKING CASE	1	BD84PU
	PC2	RPF0662	POLYETHYLENE BAG	1	
	PC3	SPN0427	CUSHION	1	
	PC4	SPN0427	CUSHION	1	

2.2. Electrical Replacement Parts List

Notes:

*Important safety notice:

Components identified by Δ mark have special characteristics important for safety.

Furthermore, special parts which have purposes of fire-retardant (resistors), high-quality sound (capacitors), low-noise (resistors), etc. are used.

When replacing any of components, be sure to use only manufacturer's specified parts shown in the parts list.

*Warning: This product uses a laser diode. Refer to caution statements.

*Capacity values are in microfarads (μ F) unless specified otherwise, P=Pico-farads (pF), F=Farads (F).

*Resistance values are in ohms, unless specified otherwise, 1K=1,000 (OHM), 1M=1,000k (OHM).

*The marking (RTL) indicates the retention time is limited for this item. After the discontinuation of this assembly in production, it will no longer be available.

*All parts are supplied by CHPAVC.

E.S.D. standards for Electrostatically Sensitive Devices, refer to "PREVENTION OF ELECTROSTATIC DISCHARGE (ESD) TO ELECTROSTATICALLY SENSITIVE (ES) DEVICES" section.

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	■	SEP0405AA	OPERATION P.C.B.		(RTL) E.S.D.
	C2001	F1H1A105A143	10V 1U	1	
	D2001	B3AAA0001018	DIODE	1	E.S.D.
	IR2001	PNJ4881M02VT	REMOTE SENSOR	1	
	JK2001	K1FY104B0104	JACK USB	1	
	P2001	SEE0157	FFC	1	
	R2001	D0GD911JA052	1/8W 910	1	
	R2002	D0GB330JA065	1/16W 33	1	
	S2001	EVQ11A05R	OPEN/CLOSE KEY	1	
	S2002	EVQ11A05R	POWER KEY	1	
	ZA2001	K9ZZ00002324	EARTH PLATE	1	
	■	SUKB404AB1UT	DIGITAL P.C.B.	1	E.S.D. ADJ BD84PU
	■	SUKB404AF1UT	DIGITAL P.C.B.	1	E.S.D. ADJ BD94PU
	■	SUKB404AB1NT	DIGITAL P.C.B.	1	E.S.D. ADJ BD84GN
	■	SUKB404AB1AT	DIGITAL P.C.B.	1	E.S.D. ADJ BD84GA/GH
	C3001	F1H1E105A153	25V 1U	1	
	C3101	F1J1C106A269	16V 10U	1	
	C3102	F1H1A105A143	10V 1U	1	
	C3103	F1H0J1060006	6.3V 10U	1	
	C3104	F1G1E682A134	25V 6800P	1	
	C3105	F1H0J1060006	6.3V 10U	1	
	C3106	F1H1C104A178	16V 0.1U	1	

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	C3201	F1J1C106A269	16V 10U	1	
	C3202	F1H1A105A143	10V 1U	1	
	C3203	F1J0J2260004	6.3V 22U	1	
	C3204	F1G1E682A134	25V 6800P	1	
	C3205	F1J0J2260004	6.3V 22U	1	
	C3206	F1H1C104A178	16V 0.1U	1	
	C3301	F1J1C106A269	16V 10U	1	
	C3302	F1H1A105A143	10V 1U	1	
	C3303	F1J0J2260004	6.3V 22U	1	
	C3304	F1G1E682A134	25V 6800P	1	
	C3305	F1J0J2260004	6.3V 22U	1	
	C3306	F1H1C104A178	16V 0.1U	1	
	C3401	F1H1A105A143	10V 1U	1	BD94PU
	C3402	F1H1C104A178	16V 0.1U	1	BD94PU
	C3501	F1J1A2250011	10V 2.2U	1	
	C3502	F1J1A2250011	10V 2.2U	1	
	C3503	F1G1C103A127	16V 0.01U	1	
	C3601	F1H1E223A050	25V 0.022U	1	
	C3602	F1H1A105A143	10V 1U	1	
	C3603	F1H1A105A143	10V 1U	1	
	C3604	F1H1C104A178	16V 0.1U	1	
	C3605	F1H1C104A178	16V 0.1U	1	
	C3701	F1J1A106A043	10V 10U	1	
	C3702	F1J1A106A043	10V 10U	1	
	C3801	F1H1A105A143	10V 1U	1	
	C4001	F1G0J1050007	6.3V 1U	1	
	C4006	F1G1C104A146	16V 0.1U	1	
	C4007	F1G0J1050007	6.3V 1U	1	
	C4008	F1G1C104A146	16V 0.1U	1	
	C4009	F1G1C104A146	16V 0.1U	1	
	C4010	F1G1C104A146	16V 0.1U	1	
	C4011	F1G1C104A146	16V 0.1U	1	
	C4022	F1H0J4750004	6.3V 4.7U	1	
	C4024	F1G0J1050007	6.3V 1U	1	
	C4025	F1G1C104A146	16V 0.1U	1	
	C4028	F1G1C104A146	16V 0.1U	1	
	C4029	F1G1C104A146	16V 0.1U	1	
	C4030	F1G1C104A146	16V 0.1U	1	
	C4032	F1G1C104A146	16V 0.1U	1	
	C4033	F1G1C104A146	16V 0.1U	1	
	C4035	F1G1C104A146	16V 0.1U	1	
	C4036	F1H0J1060006	6.3V 10U	1	
	C4037	F1G0J1050007	6.3V 1U	1	
	C4038	F1G1C104A146	16V 0.1U	1	
	C4039	F1G1C104A146	16V 0.1U	1	
	C4040	F1G1C104A146	16V 0.1U	1	
	C4041	F1G1C104A146	16V 0.1U	1	
	C4042	F1G1C104A146	16V 0.1U	1	
	C4044	F1G1C104A146	16V 0.1U	1	
	C4045	F1H0J1060006	6.3V 10U	1	
	C4046	F1J0J2260004	6.3V 22U	1	
	C4047	F1G1C104A146	16V 0.1U	1	
	C4048	F1H0J4750004	6.3V 4.7U	1	
	C5003	F1G1C104A146	16V 0.1U	1	
	C5005	F1G1C104A146	16V 0.1U	1	
	C5006	F1H0J4750004	6.3V 4.7U	1	
	C5007	F1G0J1050007	6.3V 1U	1	
	C5008	F1G1C104A146	16V 0.1U	1	
	C5009	F1G0J4750005	6.3V 4.7U	1	
	C5011	F1G1H220A774	50V 22P	1	
	C5012	F1G1C104A146	16V 0.1U	1	
	C5013	F1G1H220A774	50V 22P	1	
	C5016	F1G1C104A146	16V 0.1U	1	
	C5017	F1G1C104A146	16V 0.1U	1	
	C5018	F1G0J1050007	6.3V 1U	1	
	C5019	F1G1C104A146	16V 0.1U	1	
	C5021	F1G1C104A146	16V 0.1U	1	
	C5022	F1G0J1050007	6.3V 1U	1	
	C5028	F1G1C104A146	16V 0.1U	1	
	C6002	F1G1C104A146	16V 0.1U	1	
	C6003	F1G0J1050007	6.3V 1U	1	
	C6004	F1G1C104A146	16V 0.1U	1	
	C6006	F1G1C104A146	16V 0.1U	1	

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	C6007	FIG0J1050007	6.3V 1U	1	
	C6012	FIG1C104A146	16V 0.1U	1	
	C6013	FIG1C104A146	16V 0.1U	1	
	C6014	FIG1C104A146	16V 0.1U	1	
	C6015	FIG1C104A146	16V 0.1U	1	
	C6016	FIG0J1050007	6.3V 1U	1	
	C6017	FIG1C104A146	16V 0.1U	1	
	C7201	FIG1C104A146	16V 0.1U	1	BD84GA/ GN/GH/PU
	C7204	FIG1C104A146	16V 0.1U	1	BD84GA/ GN/GH/PU
	C8002	FIH0J225A085	6.3V 2.2U	1	
	C8003	FIH0J4750004	6.3V 4.7U	1	
	C8004	FIG1A104A058	10V 0.1U	1	
	C8005	FIH0J4750004	6.3V 4.7U	1	
	C8006	FIG1E102A134	25V 0.001U	1	
	C8009	FIH0J225A085	6.3V 2.2U	1	
	C8010	FIG1C104A124	16V 0.1U	1	
	C8011	FIG1C104A124	16V 0.1U	1	
	C8014	FIG1A104A058	10V 0.1U	1	
	C8023	FIG1C104A146	16V 0.1U	1	
	C8024	FIJ1A106A043	10V 10U	1	
	C8026	FIK1E1060001	25V 10U	1	
	C8027	FIG1C104A146	16V 0.1U	1	
	C8029	FIG1C104A146	16V 0.1U	1	
	C8030	FIG1C104A146	16V 0.1U	1	
	C8031	FIG1E102A134	25V 0.001U	1	
	C8032	FIG1E102A134	25V 0.001U	1	
	C8034	FIG1A104A058	10V 0.1U	1	
	C8036	FIJ0J2260004	6.3V 22U	1	
	C8037	F2G0J221A065	6.3V 220U	1	
	C8038	FIG1C104A146	16V 0.1U	1	
	C8039	FIG1E102A134	25V 0.001U	1	
	C8040	FIG1C104A146	16V 0.1U	1	
	C8041	FIG1E102A134	25V 0.001U	1	
	C8044	FIG0J1050007	6.3V 1U	1	
	C8045	FIG1A104A058	10V 0.1U	1	
	C8047	FIK1E1060001	25V 10U	1	
	C8048	FIG1C104A146	16V 0.1U	1	
	C8051	FIG1C104A146	16V 0.1U	1	
	C8052	FIG1C104A146	16V 0.1U	1	
	C8053	FIJ1A106A043	10V 10U	1	
	C8054	FIG1C104A124	16V 0.1U	1	
	C8055	FIG1A104A058	10V 0.1U	1	
	C8056	FIH1H682A219	50V 0.0068U	1	
	C8057	FIG1E103A134	25V 0.01U	1	
	C8058	FIG1E103A134	25V 0.01U	1	
	C8065	FIG1E102A134	25V 0.001U	1	
	C8066	FIJ1C106A269	16V 10U	1	
	C8068	FIK1E105A029	25V 1U	1	
	C8069	FIK1E1060001	25V 10U	1	
	C8070	FIG1A104A058	10V 0.1U	1	
	C8078	FIH1A225A051	10V 2.2U	1	
	C8079	FIJ1C106A269	16V 10U	1	
	C8080	FIJ1C106A269	16V 10U	1	
	FB8000	G1C100KA0101	COIL	1	
	FB8001	G1C100KA0101	COIL	1	
	FB8002	G1C220MA0291	COIL	1	
	FB8003	J0JYC0000743	COIL	1	
	FB8004	J0JYC0000743	COIL	1	
	IC3101	C0DBAYY02083	IC	1	E.S.D.
	IC3201	C0DBAYY02083	IC	1	E.S.D.
	IC3301	C0DBAYY02083	IC	1	E.S.D.
	IC3501	C0DBGYY03592	IC	1	E.S.D.
	IC3601	C0DBGYY03975	IC	1	E.S.D.
	IC3602	C0EBY0000679	IC	1	E.S.D.
	IC3701	C0DBZYY00723	IC	1	E.S.D.
	IC4001	SUKB404AF1UT	IC	1	E.S.D. ADJ BD94PU

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	IC4001	SUKB404AB1NT	IC	1	E.S.D. ADJ BD84GN
	IC4001	SUKB404AB1AT	IC	1	E.S.D. ADJ BD84GA/GH
	IC4001	SUKB404AB1UT	IC	1	E.S.D. ADJ BD84PU
	IC4002	C3ABVY000046	IC	1	E.S.D.
	IC5001	C0DBGYY03992	IC	1	E.S.D.
	IC6001	SUKB404AF1UT	IC	1	E.S.D. ADJ BD94PU
	IC6001	SUKB404AB1NT	IC	1	E.S.D. ADJ BD84GN
	IC6001	SUKB404AB1AT	IC	1	E.S.D. ADJ BD84GA/GH
	IC6001	SUKB404AB1UT	IC	1	E.S.D. ADJ BD84PU
	IC7201	G5BYC0000040	IC	1	E.S.D. BD84GA/ GH/GN/PU
	IC8001	C0GBY0000130	IC	1	E.S.D.
	IC8002	C0DBGYY02449	IC	1	E.S.D.
△	IP3001	K5H252Z00003	SURFACE MOUNT- ING FUSE	1	
△	IP3401	ERBRE1R00V	SURFACE MOUNT- ING FUSE	1	BD94PU
	J8001	K1MY45AA0310	CONNECTOR (45P)	1	
	J8002	K1MY05AA0308	CONNECTOR (5P)	1	
	J8003	K1MY05AA0308	CONNECTOR (5P)	1	
	J8004	K1MY04AA0308	CONNECTOR (4P)	1	
	JK3001	K2EDYB000005	JACK DC	1	
	JK5001	K1FY119E0067	JACK HDMI	1	
	JK7201	K2LC108E0016	JACK LAN	1	BD84GA/ GN/GH/PU
	L3101	G1C4R7MA0445	COIL	1	
	L3201	G1C3R3ZA0388	COIL	1	
	L3301	G1C3R3ZA0388	COIL	1	
	LB5001	J0ZZB0000194	COIL	1	
	LB5002	J0ZZB0000194	COIL	1	
	LB5003	J0JCC0000287	COIL	1	
	P5002	K1KY06AA0802	CONNECTOR (6P)	1	
	P7101	K1KY04AA0802	CONNECTOR (4P)	1	BD94PU
	Q3401	B1CHRD000092	TRANSISTOR	1	E.S.D. BD94PU
	Q3801	B1CHRD000092	TRANSISTOR	1	E.S.D.
	Q5001	B1GBCFJN0039	TRANSISTOR	1	E.S.D.
	Q6001	B1GDCFEJ0010	TRANSISTOR	1	E.S.D.
	QR3401	B1GBCFNN0041	TRANSISTOR	1	E.S.D. BD94PU
	QR3801	B1GBCFNN0041	TRANSISTOR	1	E.S.D.
	R3101	D0GB220JA065	1/16W 22	1	
	R3102	D1BA1203A022	1/32W 120K	1	
	R3103	D1BA2202A022	1/32W 22K	1	
	R3104	D1BA1801A022	1/32W 1.8K	1	
	R3105	D0GA103JA023	1/16W 10K	1	
	R3201	D0GB220JA065	1/16W 22	1	
	R3202	D1BA2202A022	1/32W 22K	1	
	R3203	D1BA2202A022	1/32W 22K	1	
	R3301	D1BA2202A022	1/32W 22K	1	
	R3302	D0GB470JA065	1/10W 47K	1	
	R3303	D1BA1002A022	1/32W 10K	1	
	R3304	D1BA2701A022	1/16W 2.7K	1	

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	R3401	D0GA103JA023	1/16W 10K	1	BD94PU
	R3402	D0GA473JA023	1/16W 47K	1	BD94PU
	R3601	D0GA103JA023	1/16W 10K	1	
	R3701	D0GA474JA023	1/16W 470K	1	
	R3702	D0GA183JA023	1/16W 18K	1	
	R3703	D0GBR00J0004	1/16W 0	1	
	R3704	D0GA103JA023	1/16W 10K	1	
	R3705	D0GA103JA023	1/16W 10K	1	
	R3801	D0GA473JA023	1/16W 47K	1	
	R3802	D0GA103JA023	1/16W 10K	1	
	R3803	D0GDR00J0004	1/8W 0	1	
	R4001	D0GAR00J0005	1/16W 0	1	
	R4006	D0GA241JA023	1/16W 240	1	
	R4011	D0GAR00J0005	1/16W 0	1	
	R4015	D1BA1001A022	1/32W 1K	1	
	R4016	D1BA1000A022	1/32W 100	1	
	R4018	D1BA1001A022	1/32W 1K	1	
	R4019	D1BA1200A022	1/32W 120	1	
	R4020	D1BA1001A022	1/32W 1K	1	
	R4021	D0GAR00J0005	1/16W 0	1	
	R4023	ERJ2RKD510X	1/16W 51	1	
	R5001	D0GA105JA023	1/16W 1000K	1	
	R5002	D0GA100JA023	1/16W 10	1	
	R5004	D0GA182JA023	1/16W 1.8K	1	
	R5005	D0GA182JA023	1/16W 1.8K	1	
	R5006	D0GAR00J0005	1/16W 0	1	
	R5010	D0GA103JA023	1/16W 10K	1	
	R5011	D0GA103JA023	1/16W 10K	1	
	R5013	D0GA472JA023	1/16W 4.7K	1	BD94PU
	R5014	D0GA472JA023	1/16W 4.7K	1	BD84GA/ GN/GH/PU
	R5016	D0GA472JA023	1/16W 4.7K	1	BD84GA/ GN/GH/PU
	R5017	D0GA472JA023	1/16W 4.7K	1	BD94PU
	R5019	D0GA330JA023	1/16W 33	1	
	R5029	D0GA103JA023	1/16W 10K	1	
	R5030	D0GA103JA023	1/16W 10K	1	
	R5031	D0GA103JA023	1/16W 10K	1	
	R5032	D0GA103JA023	1/16W 10K	1	
	R5033	D0GA182JA023	1/16W 1.8K	1	
	R5034	D0GA103JA023	1/16W 10K	1	
	R6001	D1BA5101A022	1/16W 5.1K	1	
	R6002	D1BA5101A022	1/16W 5.1K	1	
	R6003	D1BA2402A022	1/32W 24K	1	
	R6004	D0GA472JA023	1/16W 4.7K	1	
	R6005	D0GAR00J0005	1/16W 0	1	
	R6006	D0GA472JA023	1/16W 4.7K	1	
	R6008	D0GA103JA023	1/16W 10K	1	
	R6009	D0GA103JA023	1/16W 10K	1	
	R6010	D0GA103JA023	1/16W 10K	1	
	R6011	D1BA5101A022	1/16W 5.1K	1	
	R6012	D0GA103JA023	1/16W 10K	1	
	R6013	D0GA153JA023	1/16W 15K	1	BD84GA/ GN/GH/PU
	R6014	D0GA153JA023	1/16W 15K	1	BD84GA/ GN/GH/PU
	R6015	D0GA153JA023	1/16W 15K	1	
	R6016	D0GA153JA023	1/16W 15K	1	
	R6017	D0GA103JA023	1/16W 10K	1	
	R7201	D0GA750JA023	1/16W 75	1	BD84GA/ GN/GH/PU
	R7202	D0GA750JA023	1/16W 75	1	BD84GA/ GN/GH/PU
	R7203	D0GA750JA023	1/16W 75	1	BD84GA/ GN/GH/PU
	R7204	D0GA750JA023	1/16W 75	1	BD84GA/ GN/GH/PU
	R8002	D0GA121JA023	1/16W 120	1	
	R8004	D0GA121JA023	1/16W 120	1	
	R8005	D0GA121JA023	1/16W 120	1	
	R8013	ERJ8RQFR39V	1/2W 0.39	1	
	R8014	D0GA103JA023	1/16W 10K	1	
	R8015	ERJ8RQFR39V	1/2W 0.39	1	
	R8019	D0GA103JA023	1/16W 10K	1	
	R8023	D0GB913JA065	1/10W 91K	1	

Safety	Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	RX8000	D1H81024A042	RESISTOR-RESIS- TOR	1	
	X5001	H0J270500185	OSCILLATOR	1	